


# 433 MHz Accessories

## How do I pair / unpair a 433 MHz accessory?


First, make sure that the remote that was provided with your 433 device is paired with your device. Follow the instructions on the user guide to pair correctly.

### Pair an accessory

From the  **ARCHOS Smart Home** application, go to the 

**Accessoires** menu on the left and press  on the right top. Select the type of 433 MHz accessories that you want to add and then simply follow the pairing procedure.

With a 433 MHz accessory functioning only in one direction, you will need to confirm the record on button **(1)** and the record off button **(2)** via the remote provided by the manufacturer so the codes could be integrated to the Smart Home Tablet.

 Make sure to press only once on each button during the process because the Smart Home will save each and every input.

Put the remote control close to "Smart Home Gateway"

Press the "Record ON" button below, then you have 3 seconds to press the "ON" button on the remote control

Record ON 1

Test ON

Press the "Record OFF" button below, then you have 3 seconds to press the "OFF" button on the remote control

Record OFF 2

Test OFF

NEXT

● ● ● ●

# 433 MHz Accessories

The application will then suggest you to rename your accessory and assign it a room, the same process as for a Smart Home accessory.

## Unpair an accessory

It is the same process than for the Smart Home accessory. In the menu **Accessories**, press the name of the 433 MHz accessory than you want to unpair, a menu will be displayed, select Unpair.

Unique solution ID: #1622

Author: Admin FAQ

Last update: 2014-10-28 11:16